

Mode 1 channel	Mode 2 channel	8bit channel	Value	Function	Type of control
9	9	7	0-95 96-159	3-facet prism rotatin control,Prism macros Open position (no prism) 3-facet rotating prism	step proportional
			160-255 160-167 168-175 176-183 184-191 192-199 200-207 208-215 216-223 224-231 232-239 240-247 248-255	Prism/rot.gobo macros Macro 1 Macro 2 Macro 3 Macro 4 Macro 5 Macro 6 Macro 7 Macro 8 Macro 9 Macro 10 Macro 11 Macro 12	step step step step step step step step step step step step
10	10	8	0 1-126 127-128 129-255	3-facet prism rotation control No rotation Forwards rotation from fast to slow No rotation Backwards rotation from slow to fast	step proportional step proportional
11	11	9	0-31 32-63 64-95 96-127 128-159 160-223 224-255	Rotating gobos Open/hole Rot.gobo 1 (glass) Rot.gobo 2 (metal) Rot.gobo 3 (metal) Rot.gobo 4 (metal) Rot.gobo 5 (metal) Rot.gobo wheel cont.rotation from slow to fast	step step step step step step proportional
12	12	10	0-127 128-190 191-192 193-255	Rotating gobo index,rotating gobo rotation Gobo indexing Forwards gobo rotation from fast to slow No rotation Backwards gobo rotation from slow to fast	proportional proportional step proportional
13	13	11	0-31 32-47 48-63 64-79 80-95 96-111 112-127 128-159 160-175 176-191 192-207 208-223 224-239 240-255	Zoom,frost,UV filter <i>Zoom without focus corection</i> Zoom 15° Zoom 18° Zoom 21° Zoom 24° Zoom 26° Frost UV-filter <i>Zoom with focus corection</i> Zoom 15° Zoom 18° Zoom 21° Zoom 24° Zoom 26° Frost UV-filter	step step step step step step step step step step step step step step step

Mode 1 channel	Mode 2 channel	8bit channel	Value	Function	Type of control
14	14	12	0-255	Focus Continuous adjustment from far to near	proportional
15	15	13	0-31 32-63 64-95 96-127 128-159 160-191 192-223 224-255	Shutter, strobe Shutter closed No function (Shutter open) Strobe-effect from slow to fast (max. 10 flashes/s) No function (Shutter open) Pulse-effect in sequences from slow to fast No function (Shutter open) Random strobe-effect from slow to fast No function (Shutter open)	step step proportional step proportional step proportional step
16	16	14	0-255	Dimmer intensity Gradual adjustment of the dimmer intensity from 0 to 100%	proportional