



APM1060

COMPACT PA MIXER-AMPLIFIER 60W WITH USB, SD, BLUETOOTH, FM & REMOTE CONTROL

This mixer-amplifier is the perfect solution for small PA installations, offering a USB, SD player, Bluetooth and FM tuner in a compact housing.

FEATURES

- USB, SD, Bluetooth & FM
- Remote control
- 2 balanced mic inputs
- Priority function on MIC1, 48V phantom power on MIC2
- 2 x AUX inputs
- Line output for an extra amplifier
- High resolution display showing information on the current program
- Separate volume controls for all inputs
- Master volume
- Bass/treble tone controls
- Protections: Overheating, short-circuits, overload and peak current limiter
- Step-up transformer to comply with 70V & 100V line systems
- 4-16 Ohm output
- 100-230V~ & 24Vdc power supply

Power	60W
Outputs.....	Low impedance 4-16 Ohms
Outputs.....	Line 70V & 100V
Compatible media.....	USB, SD, Bluetooth, FM, AUX
Compatible formats	MP3, WMA, WAV, FLAC, APE
BT freq.....	2402-2480MHz
Bluetooth E.I.R.P.....	2dBm
FM freq.....	87.5-107.5MHz
Freq. range	60Hz 15kHz (+/-3dB)
S/N ratio	>= 75dB
Tone controls	Graves : 100Hz (+/-10dB) / Aigus 10kHz (+/-10dB)
Protections.....	Courts-circuits, surcharge, thermique
Power supply.....	AC: 100-230V~50Hz, 0.33A
Power supply.....	DC: 24V 3.13A
Power lead.....	3x 0.75mm ² x 1.5m



CODE: 95-1005
EAN: 5420047140500

LOGISTIC VALUES / VALEURS LOGISTIQUES

Carton dims / Dim. carton.....	34,0 x 25,5 x 11,5cm
Volume	0,010m ³
N/G weight / Poids N/B.....	2,950/3,3 kg
Carton qty.....	4