



APM1120

COMPACT PA MIXER-AMPLIFIER 120W WITH USB, SD, BLUETOOTH, FM & REMOTE CONTROL

This mixer-amplifier is the perfect solution for small PA installations, offering a USB, SD player, Bluetooth and FM tuner in a compact housing.

FEATURES

- USB, SD, Bluetooth & FM
- Remote control
- 2 unbalanced mic inputs
- Priority function on MIC1, 48V phantom power on MIC2
- 2 x AUX inputs
- Line output for an extra amplifier
- High resolution display showing information on the current program
- Separate volume controls for all inputs
- Master volume
- Bass/treble tone controls
- Protections: Overheating, short-circuits, overload and peak current limiter
- Step-up transformer to comply with 70V & 100V line systems
- 4-16 Ohm output
- 100-230V~ & 24Vdc power supply

Power	120W
Outputs.....	Low impedance 4-16 Ohms, Line 70V & 100V
Inputs.....	USB, SD, Bluetooth, FM, AUX
Bluetooth frequency band.....	2402-2480MHz
Max. RF transmission power of BT.....	2dBm
FM frequency band.....	87.5-107.5MHz
Frequency response.....	60Hz - 15kHz (+/-3dB)
Total harmonic distortion.....	< 1% @ 1kHz, 1/3 of rated power)
Signal to noise ratio.....	>= 75dB
Power supply.....	AC: 100-230V~50Hz, 0.33A DC: 24V 3.13A
Dimensions.....	300 x 191 x 71mm
Weight.....	5.5kg



BST® IS A REGISTERED TRADEMARK OF LOTRONIC SA

CODE: 95-1006
EAN: 5420047140517

LOGISTIC VALUES / VALEURS LOGISTIQUES

Carton dims / Dim. carton.....	34,0 x 25,5 x 11,5cm
Volume	0,010m ³
N/G weight / Poids N/B.....	4,250/4,6 kg
Carton qty.....	4 pcs.