



APM2826

5-ZONE PA MIXER-AMPLIFIER 240W WITH USB, BLUETOOTH, FM & REMOTE CONTROL

This 5-zone mixer-amplifier is designed for background music/paging and fits easily into a large variety of public address system designs.

FEATURES

- USB, Bluetooth & FM
- Remote control
- 3 mic inputs with Priority function on MIC1
- 2 x AUX inputs
- Line outputs for two extra amplifiers
- Separate volume controls for all inputs
- Master volume
- Bass/treble tone controls
- Protections: Overheating, short-circuits & overload
- Step-up transformer to comply with 70V & 100V line systems
- 4-16 Ohm output

Power	240W
Outputs.....	Low impedance 4-16 Ohms Line 70V & 100V
Bluetooth frequency band.....	2402-2480MHz
Max. RF transmission power of BT.....	12.48dBm
FM frequency band.....	87.5-107.5MHz
Total harmonic distortion.....	<1% @ 1kHz, 1/3 of rated power)
Frequency range.....	60Hz - 15kHz (+/-3dB)
Signal to noise ratio.....	>= 75dB
Power supply.....	230V~50Hz
Fuse.....	4A
Consumption.....	350W
Dimensions.....	483 x 366 x 89mm
Weight.....	15.4kg



BST® IS A REGISTERED TRADEMARK OF LOTRONIC SA

CODE: **95-1007**
EAN: **5420047140524**

LOGISTIC VALUES / VALEURS LOGISTIQUES

Carton dims / Dim. carton.....	52,0 x 43,5 x 18,5cm
Volume	0,042m ³
N/G weight / Poids N/B.....	12,0/13,0 kg
Carton qty.....	2 pcs.